

# Acer XL series

## Acer XL1220

# The laser projector for every requirement

With the Acer XL1220 laser projector, you'll experience all the benefits of laser projection combined with vibrant colors thanks to sRGB & Rec. 709. XGA resolution and incredible Dynamic Black contrast of 2,000,000:1 will put your presentation or the Netflix series in a new light.

If you were still undecided about switching to laser projectors, now is the time to change. The XL1220 can be turned on and off instantly and lasts up to 30,000 hours - that's 3.4 years of continuous operation!



- Light technology: Laser diode
- Resolution: XGA (1.024 x 768 px)
- Brightness: 3, 100 (standard), 2,480 (eco) ANSI lumens
- Contrast: 2,000,000:1
- Life (hr.): 20,000 (standard), 30,000 (eco)
- Warranty: 2 years PickUp service, 1 year for the lamp, 5 years for the DLP Chip



















Acer XL1220 **SPECIFICATIONS** 







Model XI 1220 Part Number MR.JTR11.001 4710886229353 FAN

Projection technology DLP 3D Ready & HDMI 3D DLP Chip 0,55" BrilliantColor™ DarkChip™ 3 DMD Version . XGA (1,024 x 768 px) Resolution 4:3 (native) / 16:9 (supported) Display Format 2,000,000:1 Contrast Displayable Colours 1.07 Billion Colors

Brightness 3,100 (standard), 2,480 (eco) ANSI lumens F = 2.41 ~ 2.53 / f = 21.85 ~ 24.01 mm Focus / Focal distance

0.64 ~ 7.62 m Projection size (diagonal) 1.20 ~ 11.80 m Projection distance 1.94~2.16:1 Throw ratio 1:1.1x/2x Zoom / Digital-Zoom Image Offset 115%

Horizontal / Vertical frequency 15 ~ 100 kHz/24 ~ 120 Hz Projection Modes 360° Projection Laser diode

Light technology 20,000 (standard), 30,000 (eco) Life (hr.) +/- 30° (vertical) manual & automatic Keystone Correction

Speaker 1x3 watt Weight / incl. packaging (kg) 4.00 kg Dimensions / Shipping dimensions (mm) 337 x 265 x 119

145 (standard), 122 (eco), < 0.5 watt Power Consumption

(standby)

Noise level 34 (standard), 29 (eco) dB

Uniformity (%) 80 % Color

HDMI with HDCP 2x VGA analog D-Sub 1x Composite Video RCA 1x Audio in (3.5mm) 1x

### Output Ports

USB Type A 1x DC Out 5V Audio out (3.5 mm) 1x D-Sub Out (for Monitor Loop Through) 1x

#### Network and Control Ports

1x USB B (Remote Computer Control) 1x

PIN security card PIN security 1x (Euro-plug) Power adapter IEC 320 C13 VGA cable 15pol 1x (1.80 m)

IR remote control incl batteries 1x (PgUp / PgDown & freeze & laserpointer function) white

Lens cap 1x Quick Start Guide 1x

4713147892877 / MC.JLC11.002 Universal ceiling mount short Universal ceiling mount long 4713147892884 / MC.JLC11.003 Acer 3D Shutterbrille 4713147532261 / MC.JFZ11.00B Acer WirelessHD Kit 4713147715251 / MC.JKY11.009 Acer CastMaster Buttons 4710180557206 / MC.40511.00N 4713883764520 / MC.JOC11.008 Acer Wireless Mirror Acer CastMaster Touch 4710180784336 / MC.40511.00Y

Warranty 2 years PickUp service, 1 year for the lamp, 5 years for the DLP Chip

#### Usage recommendation

Usage recommendation Office, home office, conference room

https://www.acer.com/ac/de/CH/content/ Projection Distance Calculator acer-projection-calculator



### Acer XL1220

### **ACCESSORIES AND FEATURES**

#### Acer Color Safe II



Acer ColorSafe II guarantees consistent, brilliant and natural color projection throughout the life of the projector. This is ensured by the use of DLP® technology and a 5-year warranty

on the DLP® chip. Projectors without DLP® technology experience a decrease in colour brilliance over time.

#### Rec. 709



Rec. 709

Rec.709 is the first worldwide uniform standard for HDTV (High Definition Television). By complying with the Rec.709 standard, the projector is able to reproduce any high-definition content, whether it is a television signal, Blu-Ray content, content from video platforms, camcorders or cameras, in the original format and with the same quality.

#### AC Power On



AC power or

With the AC Power On function, the projector is able to turn on automatically when the projector is powered. You no longer need to turn on the projector separately, but can start the projector directly, for example by turning on the power in the meeting room.

### HDMI Power On



With the HDMI Power On function, the projector is able to turn on automatically when the projector receives a signal via HDMI or VGA. You no longer need to start the projector separately, but can simply switch on your notebook, receiver or game console and the projector will automatically switch on as well.

#### Automatic Keystone Correction



Thanks to the automatic vertical keystone correction, the Acer projector automatically compensates for trapezoidal distortion if the projector is not positioned exactly vertically and projects a rectangular image.

### **Automatic Keystone Correction**



Thanks to the automatic vertical keystone correction, the Acer projector automatically compensates for trapezoidal distortion if the projector is not positioned exactly vertically and projects a rectangular image.

#### Customizable startup screen



CUSTOMIZABLE STARTUP SCREEN

The Customizable Startup Screen allows you to create an individual startup screen per screenshot. This startup screen, no matter if it is the business user's company logo or a home user's favorite photo, is automatically displayed when the projector is started.

#### 24/7 Operation



24/7 Operation

Especially

Especially for signage applications, but also for exhibitions in museums or similar, this projector can be

This projector promises maximum reliability and delivers

a brilliant image even in 24/7 continuous use.\*

used without any worries.

\* Acer recommends that the projector is switched to standby mode for 30 minutes every 7 days.

#### 360° Projection



360 degree projection

The 360° projection offers you highest flexibility and allows you to use the projector in all positions as well as to realize interesting installations. For example, you can project from the deck of the room onto the floor or a table, or mount the projector on its side to project upright.

#### HDMI 3D



HDMI 3D: The integrated HDMI 1.4a standard allows 3D content to be transferred from suitable playback devices such as 3D Blu-ray players, 3D set-top boxes and 3D game consoles without the need for an additional PC. For example, Acer 3D shutter glasses Bluray 3D movies and 3D TV shows can be viewed in your living room up to 7.62 meters (300") diagonal.

#### Acer Smart Format Technology



SmartFormat

Acer SmartFormat technology supports a wide range of input signals, eliminating the need for switching on your notebook/PC, DVD player and receiver. Signals up to 1080p can be received by Acer ColorBoost projectors with HDMI\* using Acer SmartFormat technology and can be played back in compressed form.

\*Depends on model

#### Original 24p



Experience true cinema at 24 frames per second. The Acer Blu-Ray projector reproduces films in the original cinema format as they were shot on the film set. See 24p movies through the eyes of the director.



Acer XL1220

### **ACCESSORIES AND FEATURES**

#### Instant Pack



InstantPack guarantees the lamp safety of Acer ColorBoost projectors. The current lamps from renowned manufacturers such as Osram and Philips are not damaged in the event of a sudden loss of power. (Acer recommends that the projector be powered until the fan stops) The lamp warranty is 1 year with no hour limit.

#### Acer Football Mode



Football Mod

Bring the stadium to your home with Acer Football Mode. The mode automatically adjusts image brightness, saturation, sharpness and gamma to make skin tones more vivid and greens more vivid. Ideal for football fans and sports enthusiasts.

### Wall Color Compensation



Wall-Color Compensation: Best image quality enables wall color correction on colored projection surfaces such as blackboards and wallpaper. 5 optimised wall colours can be compensated easily and without any further settings via the menu for best picture quality.

#### PIN Security



Acer PIN Security provides the ability to set a PIN to protect the Acer projector from unauthorized use and theft. A lost PIN can only be reset by the Acer Service after ownership verification.

### Auto Shutdown



The Auto Shutdown function automatically shuts down the Acer projector, if no input signal is received after a preset time. This function can be set individually via the menu and helps to save power and lamp hours.