
# Wall Mount for BenQ Short Throw Projector!

## Fast and Easy Installation to Keep Things Lookin' Great!


Designed to provide an easy and quick solution to mount a BenQ short-throw projector, this installer-friendly wall mount is smartly constructed with premium steel and aluminum to provide the strongest hold and stylishly polished with a pristine white finish to keep any room lookin' great! Together with an adjustable tilt angle of up to ± 10 degrees, you'll get to enjoy the most flexible viewing support for just about any setting!









#### Adjust Projection Angles




Sideways Rotation



Top to Bottom Angle Displacement



Horizontal Angle Motion



Horizontally Lateral Motion


Wall Mount 04-19-12-BQus



### Wall Mount for BenQ Short Throw Projector


#### Ultra Short Throw Wall Mount (0.3 Throw Ratio, P/N 5].]3A10.021)

Connection plate	Α
Material	Steel/Aluminum alloy
Weight	3.6 kg (7.93 lbs)
Size (W x H x L)	110 x 215 x 558 mm (4.3" x 8.5" x 21.9")
Maximum distance from wall	460mm (18.11")
Rotation angle	+/-10°
Load	15kg (33.07bs)
Screw	M4
Tilt angle	+/-10°




### Ultra Short Throw Wall Mount (0.4 Throw Ratio, P/N 5J.J4V10.011)

Connection plate	A
Material	Steel/Aluminum alloy
Weight	4.02 kg (8.86 lbs)
Size (W x H x L)	110 x 215 x 803mm (4.3" x 8.5" x 31.6")
Maximum distance from wall	705mm (27.7")
Rotation angle	+/-10°
Load	12kg (26.46lbs)
Screw	M4
Tilt angle	+/-10°



### Short Throw Wall Mount (0.6 Throw Ratio, P/N 5J.J4R10.011)

Connection plate	В
Material	Steel/Aluminum alloy
Weight	5.1 kg (11.24 lbs)
Size (W x H x L)	110 x 215 x 1368mm (4.3" x 8.5" x 53.8")
Maximum distance from wall	1270mm (50")
Rotation angle	+/-10°
Load	12kg (26.46lbs)
Screw	M4
Tilt angle	+/-10°



#### Guide sheet for hole drilling

Please visit www.benq.com for the latest guide sheet for hole drilling

	<u> </u>		
Connection plate A	Mark A ==> MX880UST Mark B ==> MX850UST / MW851UST		
Connection plate B	Mark A ==> MP772ST /MP776ST / MP782ST/ MX810ST/ MW811ST/ MX812ST / MX813ST  Mark B ==> MW814ST/LX60ST/LW61ST/MX815ST/MX816ST  Mark C ==> MP780ST/MW860USTi/MP780ST+		
Connection plate A OB OA A OA A OB		Connection plate B  A  A  B  C  B  C  C  B  C  C  C  C  C  C  C	

