

### **Model Name**

### W1500 Home Entertainment Projector

### Unique selling point

- \* Perfect for home entertainment
- \* Cable free
- Built-in two 10W Big Speakers w/ SRS
- Built-in Uncompressed Wireless FHD (WHDI)
- \* Easy Setup
  - Vertical Lens Shift (110%-130%±5%)
  - Big Zoom (1.6X)

- \* Brilliant Image Performance
  - Blu-ray Full HD 3D support
  - 2D to 3D conversion
  - Frame interpolation (MEMC)
  - Enhanced Contrast (Darkchip3)
  - Brilliant Color (REC 709)
  - Professional picture adjustment (ISFccc)

### Trade Mark













| 1996   170 x 190  | Projection System                   | Single () 45" DC3 DLP DMD        |                                     |                           |                        |  |  |  |
|---|-------------------------------------|----------------------------------|-------------------------------------|---------------------------|------------------------|--|--|--|
| 1988     |                                     |                                  | Single 0.65" DC3 DLP DMD            |                           |                        |  |  |  |
| 1000    100   |                                     |                                  |                                     |                           |                        |  |  |  |
| 100   | -                                   |                                  |                                     |                           |                        |  |  |  |
| Page     |                                     |                                  |                                     |                           |                        |  |  |  |
|   |                                     |                                  |                                     |                           |                        |  |  |  |
| 107-17   64° B) 21°   | ens                                 | F=2.45-3.07 , f=15.78-25.12mm    | 1                                   |                           |                        |  |  |  |
| Marie   100-1905  | spect Ratio                         | Native 16:9 (5 aspect ratio sele | ectable)                            |                           |                        |  |  |  |
| 1968   1969     | hrow Ratio                          | 1.07-1.71 (84"@2M)               |                                     |                           |                        |  |  |  |
|   | ffset                               | 110%~130%                        |                                     |                           |                        |  |  |  |
| 1400     | nage Size (Diagonal)                | 40"-300"                         |                                     |                           |                        |  |  |  |
|   | oom Ratio                           | 1.6:1                            |                                     |                           |                        |  |  |  |
|   | атр Туре                            | 240W                             |                                     |                           |                        |  |  |  |
| Septemblin   Se   | amp(Normal/Economic/SmartEco Mode)* | 3500/5000/6000 hours             |                                     |                           |                        |  |  |  |
| SK-100KHz   Strictal Scan Rate   Strictal Scan R   | eystone Adjustment                  | ID, Vertical ± 10 degrees        |                                     |                           |                        |  |  |  |
| 154-10264-  154-  | ens Shift                           | Vertical 110%-130%±5%            | ·                                   |                           |                        |  |  |  |
| 1854   1954     | esolution Support                   | up to WUXGA                      |                                     |                           |                        |  |  |  |
| 21-120Hz  oftow Wheel Sgement  oftow Wheel Sgement  oftow Wheel Sgement  Act (SBMCs)  Wheel Speed  Act (SBMCs)  Wideo  In Direct Compatibility  All |                                     | 15K-102KHz                       |                                     |                           |                        |  |  |  |
|   |                                     | 23-120Hz                         |                                     |                           |                        |  |  |  |
| Mary Minest Speed  May 100 May 276, 256, 256, 250, 1000, 1000 →  May 100 May 276, 256, 250, 1000, 1000 →  May 100 May 276, 256, 250, 1000, 1000 →  May 100 May 276, 1000, 100 |                                     |                                  |                                     |                           |                        |  |  |  |
| ### Note Compatibility   Nides Compatibility   Nides Compatibility   Nides Compatibility   Nides Compatibility   Nides Compatibility   Nides Park SECAN, SDTY (#80p/576p, HDTY (720p, 1080in) 60Hz) ( | -                                   |                                  |                                     |                           |                        |  |  |  |
| Video Compatibility   STC, PAL, SECAM, SDTY(480/576), EDTY (420p.1080/p 60Hz)   Parame Facine (   |                                     |                                  | 480i, 480p, 576i, 576p, 720p, 1080i | . 1080p                   |                        |  |  |  |
| SD Compatibility (Please refer to Mer's Munic (Please in (Please))   10 to 40 to 50 to 40 to 50 to 40 to 50 t  | onpatibility                        |                                  |                                     |                           |                        |  |  |  |
| Tame Packing Up to 24 Hz 1080p   Farme  |                                     |                                  |                                     | 61), EDTV (480p/576p, HDT | v (720p, 1080i/p 60Hz) |  |  |  |
| Please refor to User's Manual   See   |                                     |                                  |                                     |                           |                        |  |  |  |
| Top   Section   Top   Sectio  |                                     | (Please refer to User's Manual   |                                     |                           |                        |  |  |  |
| Computer in (D-sub 15pin)   x   |                                     | Control of the control of        |                                     |                           |                        |  |  |  |
| HDM  (v1.4a)  |                                     |                                  | 10p Bottoiii. Op to 24H2 1080p      |                           |                        |  |  |  |
| Composite Video in (RCA)  | terface                             |                                  |                                     | x I                       |                        |  |  |  |
| S-Video in (Mini DIN 4pin)   x   1  |                                     | HDMI (v1.4a)                     |                                     | x 2                       |                        |  |  |  |
| Component Video in  |                                     | Composite Video in (RCA)         |                                     | хI                        |                        |  |  |  |
| Audio In (Mini Jack) x 1 Audio In (RCA) x 1 Audio UR in (RCA) x 1 Speaker 100 x 2 RS232 (DB-9pin) x 1 RS232 (DB-9pin) x 1 Power Consumption 397W(typical), Standby<0.5 W Immensions Diemensions W H x D) 337W(typical), Standby<0.5 W Weight 39 x 120.2 x 284.8 mm Weight 39 x 120.2 x 284.8 mm Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greel/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition Chinese (28 Languages)  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greel/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition Chinese (28 Languages)  Standard Optional Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit PiN: 5,j./4N10.001 Power Cord (by region) User Manual CD (24L) Quick Sart Guide (28L) Warranty Card (by region) Lens cover VGA (D-tub 15pin) Cable   |                                     | S-Video in (Mini DIN 4pin)       |                                     | хI                        |                        |  |  |  |
| Audio L/R in (RCA) x l  Audio out (Mini Jack) x l  DC 12V Trigger (3.5mm Jack) x l  Audio L/R in (RCA) x l  Audio L/R in (RCA) x l  Speaker 100V x 2  RS232 (DB-9pin) x l  Power Supply AC 100 to 240 V, 50/60 Hz Power Consumption 397W(typical), Standby-0.5VW  Immensions Dimensions(W x H x D) 339 x 120.2 x 284.8 mm Weight 33/8 dBA (Normal/Economic mode)  Avabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition Chinese (28 Languages)  icture Modes Dynamic / Standard / Cinema / User I / User 2 / User 3 / 3D / ISF Night / ISF Day  ccessories Standard / Cinema / User I / User 2 / User 3 / 3D / ISF Night / ISF Day  ccessories Standard / Cinema / User I / User 2 / User 3 / 3D / ISF Night / ISF Day  ccessories Cortro lw/ Battery (full type, RCV011) Spar Lamp Kit Pink: 5],9E05.001  Carry bag Optional  Remote Contro lw/ Battery (full type, RCV011) Spar Lamp Kit Pink: 5],9E05.001  Carry bag Optional  Carry bag Optional  Quick Start Guide (28L)  Warranty Card (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable   |                                     | Component Video in               |                                     | хI                        |                        |  |  |  |
| Audio out (Mini Jack) x l  DC 12V Trigger (3.5mm Jack) x l  Audio L/R in (RCA) x l  Audio L/R in (RCA) x l  Speaker 10W x 2  RS232 (DB-9pin) x l  Power Cord (by region)  Arabic/Bulgarian/ Croatian / User / User 3 / 3D / ISF Night / ISF Day  Coccessories Standard Development of the power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Quick Start Guide (28L)  Ver York (2016)  Quick Start Guide (28L)  Ver York (2016)  Quick Start Guide (28L)  Ver York (2016)  Eners cover VGA (D-sub 15pin) Cable  |                                     | Audio in (Mini Jack)             |                                     | хI                        |                        |  |  |  |
| DC 12V Trigger (3.5mm Jack) x 1 Audio L/R in (RCA) x 1  Speaker 100W x 2  R5232 (DB-9pin) x 1  Ower R529ply AC 100 to 240 V, 50/60 Hz Power Consumption 377W(typical), Standby<0.5W  imensions Dimensions(W x H x D) 339 x 120.2 x 284.8 mm Weight 3,9KG  udible Noise 33/28 dBA (Normal/Economic mode)  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition Chinese (28 Languages)  icture Modes Dymanic / Standard / Cimena / Userl / User2 / User3 / 3D / ISF Night / ISF Day  ccessories Standard Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit P/N: 5J,9E05.001  Carry bag Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   |                                     | Audio L/R in (RCA)               |                                     | x I                       |                        |  |  |  |
| DC 12V Trigger (3.5mm Jack) x 1 Audio L/R in (RCA) x 1  Speaker 100W x 2  R5232 (DB-9pin) x 1  Ower Power Consumption 397W(typical), Standby<0.5W  imensions Dimensions(W x H x D) 39 x 120.2 x 284.8 mm Weight 39 x 120.2 x 284.8 mm Weight 39 x 120.2 x 284.8 mm Japanese/ Korean/ Normal/Economic mode)  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Traditions Chinese (28 Languages)  icture Modes Dynamic / Standard / Cinema / User/ / User/ / User/ 3 / 3D / ISF Night / ISF Day  ccessories Standard Power Control w/ Battery (full type, RCV011) Spare Lamp Kit P/N: 5J,9E05.001  Carry bag Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable  |                                     | Audio out (Mini lack)            |                                     | x I                       |                        |  |  |  |
| Audio L/R in (RCA) x   1  Speaker 10W x 2  RS232 (DB-9pin) x   1  Ower 1  Power Copply AC (100 to 240 V, 50/60 Hz  Power Consumption 397W(typical), Standby<0.5W  Immensions Dimensions(W x H x D) Weight 3,9KG  udible Noise 33/28 dBA (Normal/Economic mode)  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Traditions  icture Modes Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  ccessories Standard Optional  Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit P/N: 5J,J9E05.001  Carry bag Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   |                                     |                                  |                                     |                           |                        |  |  |  |
| Speaker  R5232 (DB-9pin)  x I  ower  Power Supply AC 100 to 240 V, 50/60 Hz  Power Consumption  37W (typical), Standby<0.5W  imensions  Dimensions(W x H x D) Weight 3,9KG  udible Noise  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Traditions Chinese (28 Languages)  icture Modes  Dynamic / Sandard / Cinema / User / User 2 / User 3 / 3D / ISF Night / ISF Day  Ccessories  Standard  Remote Control w/ Battery (full type, RCV011)  Carry bag  Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   |                                     |                                  |                                     |                           |                        |  |  |  |
| RS232 (D8-9pin) x   1  nower Supply AC 100 to 240 V, 50/60 Hz  Power Consumption 397W(typical), Standby<0.5W  imensions Dimensions(W x H x D) 339 x 120.2 x 284.8 mm  Weight 3,9KG  udible Noise 33/28 dBA (Normal/Economic mode)  Arabic/Bulgaran/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Traditions Chinese (28 Languages)  icture Modes Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  Ccessories Standard Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit PN: 5J,9E05.001  Carry bag Ceiling Mounting Kit P/N: 5J,94N10.001  Power Cord (by region)  User Manual CD (241)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable   |                                     | Audio L/R in (RCA)               |                                     | хI                        |                        |  |  |  |
| Power Consumption 397W(typical), Standby<0.5W   Power Consumption and Post Post Portugueses   Power Consumption and Post Post Portugueses   Power Consumption and Post Post Portugueses   Power Consumption and Post Post Post Post Post Post Post Post   |                                     | Speaker                          |                                     | 10W x 2                   |                        |  |  |  |
| Power Consumption 397W(typical), Standby<0.5W   Power Consumption and Post Post Portugueses   Power Consumption and Post Post Portugueses   Power Consumption and Post Post Portugueses   Power Consumption and Post Post Post Post Post Post Post Post   |                                     | RS232 (DB-9pin)                  |                                     | x I                       |                        |  |  |  |
| Power Consumption Dimensions(W x H x D) Weight 339 x 120.2 x 284.8 mm Weight 3,9KG  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hin-di/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Traditions Chinese (28 Languages)  Cuture Modes Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  Cuture Modes Coessories Standard Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit Power Cord (by region) User Manual CD (241) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   | nwer                                |                                  |                                     |                           | Hz                     |  |  |  |
| Dimensions (W x H x D) 339 x 120.2 x 284.8 mm Weight 3.9KG  udible Noise 33/28 dBA (Normal/Economic mode)  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition: Chinese (28 Languages)  icture Modes Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  ccessories Standard Optional  Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit P/N: 5J,J8E05.001  Carry bag Ceiling Mounting Kit P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  | V                                   |                                  |                                     |                           |                        |  |  |  |
| Weight 3,9KG  udible Noise  33/28 dBA (Normal/Economic mode)  Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition: Chinese (28 Languages)  icture Modes  Dynamic / Standard / Cinema / User / / User 2 / User 3 / 3D / ISF Night / ISF Day  ccessories  Standard Optional  Remote Control w/ Battery (full type, RCV011)  Carry bag Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable  | imensions                           |                                  |                                     |                           |                        |  |  |  |
| Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition: Chinese (28 Languages)  icture Modes  Dynamic / Standard / Cinema / User / User 2 / User 3 / 3D / ISF Night / ISF Day  Ccessories  Standard  Optional  Remote Control w/ Battery (full type, RCV011)  Carry bag  Ceiling Mounting Kit  P/N: 5J.J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  | ALLICHSIONS                         |                                  |                                     |                           |                        |  |  |  |
| Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition Chinese (28 Languages)  Dynamic / Standard / Cinema / User! / User2 / User3 / 3D / ISF Night / ISF Day  Ccessories  Standard  Remote Control w/ Battery (full type, RCV011)  Carry bag  Ceiling Mounting Kit  P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  | 1911 AL 1                           |                                  | mods)                               | J.7NG                     |                        |  |  |  |
| Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Tradition: Chinese (28 Languages)  icture Modes  Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  Ccessories  Standard  Optional  Remote Control w/ Battery (full type, RCV011)  Carry bag  Ceiling Mounting Kit  P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable   | udible Noise                        | 33/28 dBA (Normal/Economic I     | mode)                               |                           |                        |  |  |  |
| Chinese (28 Languages)  icture Modes  Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  Standard  Optional  Remote Control w/ Battery (full type, RCV011)  Carry bag Ceiling Mounting Kit P/N: 5J,J4N10.001  Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   |                                     |                                  |                                     |                           |                        |  |  |  |
| Dynamic / Standard / Cinema / User1 / User2 / User3 / 3D / ISF Night / ISF Day  Standard  Remote Control w/ Battery (full type, RCV011)  Carry bag  Ceiling Mounting Kit  P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  | On-Screen Display Languages         |                                  |                                     |                           |                        |  |  |  |
| Standard Optional  Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit P/N: 5J,J9E05.001  Carry bag Ceiling Mounting Kit P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  |                                     | Cninese (28 Languages)           |                                     |                           |                        |  |  |  |
| Standard Optional  Remote Control w/ Battery (full type, RCV011) Spare Lamp Kit P/N: 5J,J9E05.001  Carry bag Ceiling Mounting Kit P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  | icture Modes                        | Dynamic / Standard / Cinema /    | User1 / User2 / User3 / 3D / ISF Ni | ght / ISF Day             |                        |  |  |  |
| Remote Control w/ Battery (full type, RCV011)  Carry bag  Ceiling Mounting Kit  P/N: 5J,J4N10.001  Power Cord (by region)  User Manual CD (24L)  Quick Start Guide (28L)  Warranty Card (by region)  Lens cover  VGA (D-sub 15pin) Cable  |                                     |                                  | . 212.2. 200.07.00 710 141          | •                         |                        |  |  |  |
| Carry bag Celling Mounting Kit P/N: 5J,J4N10.001 Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   |                                     |                                  | ull type, RCV011)                   | •                         | P/N:- 51 19E05 001     |  |  |  |
| Power Cord (by region) User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable  |                                     | , ,                              | 71-1                                |                           |                        |  |  |  |
| User Manual CD (24L) Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable   |                                     |                                  |                                     | Cennig Flounting NIE      | 171N. JJ.JTINIO.001    |  |  |  |
| Quick Start Guide (28L) Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable  |                                     |                                  |                                     |                           |                        |  |  |  |
| Warranty Card (by region) Lens cover VGA (D-sub 15pin) Cable  |                                     |                                  |                                     |                           |                        |  |  |  |
| Lens cover<br>VGA (D-sub I Spin) Cable  |                                     |                                  |                                     |                           |                        |  |  |  |
| VGA (D-sub 15pin) Cable   |                                     |                                  |                                     |                           |                        |  |  |  |
|   |                                     |                                  |                                     |                           |                        |  |  |  |
| WHDI Wireless Dongle Kit box  |                                     |                                  |                                     |                           |                        |  |  |  |
|   |                                     | WHDI Wireless Dongle Kit bo      | ×                                   |                           |                        |  |  |  |

### \*Lamp life results will vary depending on environmental conditions and usage. Actual product's features and specifications are subject to change without notice.

\* WI500 has a built-in wireless HDMI receiver. To prevent signal interference with the projected image, please make sure there are no other devices that support 5GHz wireless signals within 3 meters from the projector, as they may potentially cause signal interference and impact the projected image. This includes but not limited to access points/routers, wireless cards/dongles, 5.8GHz wireless mouses, 5.8GHz digital phones, some Wimax products, some Autopass cards, the WI500 projectors which are performing wireless projection or devices with 802.1 IAC Wi-Fi. The suggested distance for such devices would be over 3 meters away from the projector.

If you are experiencing serious SGHz signal interference, which may be indicated by blank or persistently noise, it is recommended that you execute any of the following tips to re-build the wireless connection:

1. Change the signal source then switch back to wireless transmission to reset the projection. Just press SOURCE on the projector or remote control to display the source selection bar, and select Wireless again to re


- Disconnect the Wireless Transmitter and then replug it into the HDMI device.
   Restart the projector to reset the connection.
   If the connection still fails, please follow the procedures in user manual to redo the pairing of transmitter and receiver.

# **W1500 Home Entertainment Projector**


# **Distance Chart**

Projection dimensions

Installation for a 16:9 ratio screen



Coiling Installation



■ The screen aspect ratio is 16:9 and the projected picture is 16:9


| Screen dimensions                       |                            | Projection                | Projection distance <d> [mm]</d>   |         |                                    |   |
|---|----------------------------|---------------------------|------------------------------------|---------|------------------------------------|---|
| Diagonal<br><a><br/>[inch<br/>(mm)]</a> | Height<br><b><br/>[mm]</b> | Width<br><c><br/>[mm]</c> | Min distance<br>(with max<br>zoom) | Average | Max distance<br>(with min<br>zoom) | Lowest/Highest<br>lens position<br><e> [mm]</e> |
| 42 (1067)                               | 523                        | 930                       | 1000                               | 1300    | 1600                               | 26  |
| 50 (1270)                               | 623                        | 1107                      | 1190                               | 1548    | 1905                               | 31  |
| 60 (1524)                               | 747                        | 1328                      | 1429                               | 1857    | 2286                               | 37  |
| 70 (1778)                               | 872                        | 1550                      | 1667                               | 2167    | 2667                               | 44  |
| 80 (2032)                               | 996                        | 1771                      | 1905                               | 2476    | 3048                               | 50  |
| 84 (2134)                               | 1046                       | 1860                      | 2000                               | 2600    | 3200                               | 52  |
| 90 (2286)                               | 1121                       | 1992                      | 2143                               | 2786    | 3429                               | 56  |
| 100 (2540)                              | 1245                       | 2214                      | 2381                               | 3095    | 3810                               | 62  |
| 110 (2794)                              | 1370                       | 2435                      | 2619                               | 3405    | 4190                               | 68  |
| 120 (3048)                              | 1494                       | 2657                      | 2857                               | 3714    | 4571                               | 75  |
| 130 (3302)                              | 1619                       | 2878                      | 3095                               | 4024    | 4952                               | 81  |
| 140 (3556)                              | 1743                       | 3099                      | 3333                               | 4333    | 5333                               | 87  |
| 150 (3810)                              | 1868                       | 3321                      | 3571                               | 4643    | 5714                               | 93  |
| 160 (4064)                              | 1992                       | 3542                      | 3810                               | 4952    | 6095                               | 100   |
| 170 (4318)                              | 2117                       | 3763                      | 4048                               | 5262    | 6476                               | 106   |
| 180 (4572)                              | 2241                       | 3985                      | 4286                               | 5571    | 6857                               | 112   |
| 190 (4826)                              | 2366                       | 4206                      | 4524                               | 5881    | 7238                               | 118   |
| 200 (5080)                              | 2491                       | 4428                      | 4762                               | 6190    | 7619                               | 125   |
| 250 (6350)                              | 3113                       | 5535                      | 5952                               | 7738    | 9524                               | 156   |

The above numbers are approximate and may be slightly different from the actual measurements. Only the recommended screen sizes are listed. If your screen size is not in the table above, please contact your dealer for assistance.

# Wall mount/Ceiling mount Chart

© Ceiling Mount screw: M4 (Max L = 8 mm)

#### Unit: mm



## Dimension







